

Global Preferences

This page describes global preferences and instructs on how you can customize them.

- Set up preferences
 - Aastra
 - Cisco
 - Escene
 - Fanvil
 - Grandstream
 - Linksys
 - Panasonic
 - Polycom
 - Snom
 - Spectralink
 - Thomson
 - Tiptel
 - XRS
 - Yealink

Set up preferences

To access them, click the **Global Preferences** icon in the **Equipment Templates** management page.

The **Global Preferences** pop-up window allows you to set up the following provisioning options:

- **Provisioning system IP or hostname:** Fill in the IP address or the hostname of the server that will answer to the provisioning requests initiated by the SIP devices.
- **Allow MAC based provisioning on HTTP(S):** This generates the provisioning files required for the automatic configuration of the devices, based on their MAC address and using the Hypertext Transfer Protocol (Secure).

Security Note

 This method is considered less secure because the phone terminal's MAC address is easy to find within a network and, therefore, the configuration file is more exposed than in other circumstances.

Aastra

Model	Firmware
9122i	1.4.1 and above
9133i	1.4.1 and above
480i	1.4.1 and above
480i CT	1.4.1 and above
51i	2.3.x

Cisco

Model	Firmware
7940	7.x/8.x
7960	7.x/8.x
SPA504G	7.4.x

Escene

Model	Firmware
ES410	2.2.7.x
ES620	2.2.7.x

Panasonic

Model	Firmware
KX-UT670	01.05.x
KX-UT123	01.133

Polycom

Model	Firmware
IP 501	1.6.x/3.1.x
IP 550	2.1.x/3.3.x
IP 650	3.2.x/3.3.x
Soundpoint 300/301	1.6.x/3.1.x
Soundpoint 330/320	2.1.x/3.3.x
Soundpoint 321/331	3.3.x
VVX 3XX	5.2.x.x

Snom

Model	Firmware
300	6.2 and above

Fanvil

Model	Firmware
C62	2.2
C56	2.2.16.x

320	6.2 and above
360	6.2 and above
M3	2.x and above

Grandstream

Model	Firmware
Handy Tone 286	1.0.8.23 and above
Handy Tone 486	1.0.8.32 and above
Handy Tone 488	1.0.3.48 and above
Handy Tone 502*	1.0.3.10 and above
GXP-2000	1.2.x.x
GXP-2020	1.2.x.x

Spectralink

Model	Firmware
Spectralink 8440	4.6.x

Thomson

Model	Firmware
ST2030S	1.6.x

Tiptel

Model	Firmware
IP280	6.x.x.x
IP284	6.x.x.x
IP286	6.x.x.x

XRS

Model	Firmware
5440	2.2.7

Yealink

Model	Firmware
SIP-T20P	6.x.x.x/7.70.x.x
SIP-T22P	6.x.x.x/7.70.x.x
SIP-T26P	6.x.x.x/7.70.x.x
SIP-T28P	6.x.x.x/7.70.x.x

Linksys

Model	Firmware
SPA-122	1.3.5
SPA-901	4.1.11 and above
SPA-921	4.1.10 and above
SPA-922	4.1.10 and above
SPA-941	4.1.10 and above
SPA-942	4.1.10 and above
SPA-962	4.1.10 and above
PAP-2T	5.1.x and above
SPA2102	5.2.x and above
SPA8000	5.1.x and above

Related topics

[Customize Template Files](#)

[Import Configuration Files](#)

[Add Provisioning Templates](#)

[Manage Templates](#)