User Email Templates

This page contains instructions on how to edit email notifications and the tags required for the customization of user email templates.

- Overview
- Edit a template
- Template types
- Restore default settings

Overview

To access the **Email Templates Management** page, go to **Unified Communications** option in the side menu and click on the <u>Email Templates</u> icon under the **System Templates** area.

VoipNow can email these notifications to the system administrator(s), the service providers and/or to a custom email address.

Edit a template

To customize the subject or the content of an email notification:

- Click the icon corresponding to the chosen event.
- 2. In the Edit Email Template page, enter the email subject and body keeping in mind that:
 - You may use only plain text when writing the email subject and body. The email is also sent in plain text format.
 - You can include tags that will be automatically replaced by the system with the appropriate content (e.g. [recipient_name] is replaced with the name of the person receiving the notification).
- 3. Click OK to save the changes to the email template. To return to the previous page without saving the changes, click Cancel.

Template types

VoipNow comes with several email templates, depending on the event they are related to.

• User account creation: This email notification is sent when a new user account is created. Extension related tags are only displayed if an extension was attached to the user account on creation.

Tag	Details
[contac t_name]	The name of the contact person specified in the provided user information.
[recipi ent_nam e]	The name of the person who receives the email.
[login]	The username that will be used to connect to the user account, as it was specified in the provided user information.
[password]	The password that will be used to connect to the user account, as it was specified in the provided user information.
[billin g_plan]	The name of the billing plan employed for this particular account.
[templa te]	The name of the user template used to create this account.
[interf ace_lan guage]	The language used by the VoipNow Professional interface when this user is logged in.
[compan y_name]	The name of the company, as it was specified in the provided user information.
[contac t_name]	The name of the contact person specified in the provided user information.
[phone]	The account owner's telephone number, as it was specified in the provided user information.
[fax]	The account owner's fax number, as it was specified in the provided user information.
[addres	The account owner's address, as it was specified in the provided user information.

[email]	The account owner's email address, as it was specified in the provided user information. Please note that the email address can contain characters from any official language script. Domain names that contain these special, so called non-ASCII, characters are called Internationalized Domain Names (IDNs). VoipNow supports IDNs.
[city]	The account owner's city of residence, as it was specified in the provided user information.
[state]	The account owner's state of residence, as it was specified in the provided user information.
[country]	The account owner's country of residence, as it was specified in the provided user information.
[zip]	The account owner's postal/zip code, as it was specified in the provided user information.
[notes]	The notes/comments that were filled in the provided user information.
[ext_ty pe]	The type of the user's extension that has just been created. Displayed on extension creation only.
[ext_la bel]	The label of the user's extension that has just been created. Displayed on extension creation only.
[phone_ login]	The password used when the user registers and/or makes calls using a SIP phone. Displayed on extension creation only.
[phone_ passwor d]	The phone terminal password. Displayed on extension creation only.
[ext_nu mber]	The telephone number assigned to the newly created extension. Displayed on extension creation only.
[public _number]	The number used on the public phone network for this extension. Displayed on extension creation only.
[phone_ lang]	The language the phone interface is displayed in. Displayed on extension creation only.

• User account expiration warning: This email notification is sent <x> days in advance before the user account expires. The <x> days in advance condition is specified in the **Preferences** section.

Tag	Details
[contact_name]	The name of the user whose user account is set to expire. This is the name specified in the provided user information.
[recipient_name]	The name of the person who receives the email.
[company_name]	The name of the company, as it was specified in the provided user information.
[login]	The username used to connect to the user account, as it was specified in the provided user information.
[expire_date]	The date when the account expires.

• User account expired: This email notification is sent after the user account has expired.

Tag	Details
[contact_name]	The name of the user whose user account has just expired. This is the name specified in the provided user information.
[recipient_name]	The name of the person who receives the email.
[company_name]	The name of the company, as it was specified in the provided user information.
[login]	The username used to connect to the user account, as it was specified in the provided user information.
[expire_date]	The date when the account expired.

• User charging limit exceeded: This email notification is sent when the number of minutes available is <0> and/or the credit is <0>.

Tag	Details
[contact_na me]	The name of the contact person specified for the user account whose credit/number of minutes is below the customized limit. This is the name specified in the provided user information.
[recipient_ name]	The name of the person who receives the email.

[company_na me]	The name of the company, as it was specified in the provided user information.
[login]	The username used to connect to the user account, as it was specified in the provided user information.
[minutes_ou t]	The number of outgoing minutes left for this account.
[money_left]	The credit for outgoing calls currently available to this account.
[money]	The currency used in the system.
[month]	The month when the notification is sent.
[minutes_li mit]	The minutes limit specified in the Send charging limit warnings when the account is below field.
[money_limit]	The credit limit specified in the Send charging limit warnings when the account is below field.

• User charging limit warning: This email notification is sent when the number of minutes available is <0> and/or the credit is <0>.

Tag	Details
[contact_name]	The name of the contact person specified for the user account whose credit/number of minutes exceeded the customized limit. This is the name specified in the provided user information.
[recipient_nam e]	The name of the person who receives the email.
[company_name]	The name of the company, as it was specified in the provided user information.
[login]	The username used to connect to the user account, as it was specified in the provided user information.
[minutes_out]	The number of outgoing minutes left for this user.
[money_left]	The credit for outgoing calls currently available to this user.
[money]	The currency used in the system.
[money_left_in coming]	The credit for incoming calls currently available to this user.
[month]	The month when the notification is sent.
[minutes_limit]	The minutes limit specified in the Send charging limit warnings when the account is below field.
[money_limit]	The credit limit specified in the Send charging limit warnings when the account is below field.

• Extension creation: This email notification is sent when a new extension is created.

Tag	Details
[ext_ type]	The type of extension that has just been created.
[ext_ numbe r]	The telephone number assigned to the newly created extension.
[reci pient _name]	The name of the person who receives the email.
[cont act_n ame]	The name of the contact person specified in the provided extension information.
[ext_ label]	The extension's descriptive name.
[phon e_log in]	The phone terminal username.

[phon e_pas sword]	The phone terminal password.
[public_number]	The number used on the public phone network for this extension.
[phon e_lan g]	The language the phone interface is displayed in.
[comp any_n ame]	The name of the company, as it was specified in the provided extension information.
[phon e]	The extension owner's telephone number, as it was specified in the provided account information.
[fax]	The extension owner's fax number, as it was specified in the provided account information.
[addr ess]	The extension owner's address, as it was specified in the provided account information.
[emai 1]	The extension owner's email address, as it was specified in the provided account information. Please note that the email address can contain characters from any official language script. Domain names that contain these special, so called non-ASCII, characters are called Internationalized Domain Names (IDNs). VoipNow supports IDNs.
[city]	The extension owner's city of residence, as it was specified in the provided account information.
[stat e]	The extension owner's state of residence, as it was specified in the provided account information.
[coun try]	The extension owner's country of residence, as it was specified in the provided account information.
[zip]	The extension owner's postal/zip code, as it was specified in the provided account information.
[note s]	The notes/comments that were filled in the extension owner's provided account information.

Restore default settings

To restore the default notification settings and email contents, click the <u>Default</u> icon. This will not overwrite the other email address destination.

Related topics

Customize notification settings

Set Unified Communications email templates

Set security email templates