

extension.sh

This script allows you to create a new extension, update the extension's options, or remove an extension.

- [Usage](#)
- [Examples](#)

Usage

`/usr/local/voipnow/bin/extension.sh[options]`
where `<command>` is one of:

Argument	Parameter	Description
-h, --help		Shows the help message.
-c, --create	number	Creates a new extension.
-u, --update	number	Updates an extension.
-r, --remove	extendednumber	Removes an extension.

and available [options] are:

Argument	Parameter	Description
--auto	<empty>	Automatic password generation.
--password	password	Password used for logging in to the phone.
--parent_login	string	Login name of the user that creates this extension (required for create and update operation).
--label	string	Extension label (default to number on extension creation).
--type	string	Extension type (required for creation).
--extension_template_id	number	ID of extension template.

Examples

Add New Extension

`/usr/local/voipnow/bin/extension.sh --create 010 --parent_login newqueue --label "Queue Extension" --type "queue"`

Update Extension

`/usr/local/voipnow/bin/extension.sh --update 010 --label "First Queue"`

Remove Extension

`/usr/local/voipnow/bin/extension.sh --remove 0040*010`